


Technical Data



IP code

IP54

ARTICLE INFO

The AM-600 security cut-off module is connected between the actuator and the electrical control device. Operating the actuator in "OPEN" direction takes place without security cutoff. In the "CLOSE" direction, a safety shutdown occurs if a safety contact (e.g. contact strips or light curtains) is triggered or there is a line interruption. In this case, the actuator is switched off. Further actuation is then only possible in the "OPEN" direction. In order to release the contact in the "CLOSE" direction again, give a command "OPEN" direction or a "STOP" signal through the electrical control unit.

TECHNICAL DATA

| | |
|-------------------------------|-----------------------|
| Matchcode | Safety cut-off AM-600 |
| Article name | Safety cut-off AM-600 |
| Part number | M2 3140 |
| IP code | IP54 |
| Housing | Surface housing |
| Housing type | Plastic |
| Colour | Grey |
| Housing length | 90 |
| Housing width | 90 |
| Housing height | 45 |
| Environment temperature range | -5 °C bis 40 °C |